

## Rugged DC/DC Auto Power Adapter

### For Motion Computing TabletPCs

The Lind Automobile Power Adapter delivers a true continuous 95 Watt power output to your notebook. The Adapter allows the device to be operated and its internal battery to be recharged from any 12-32 VDC source. Simply plug the Lind Automobile Power Adapter into the cigarette lighter socket in an automobile and into the power jack of the notebook. The adapter adjusts, conditions and regulates the power from the input to the correct DC voltage required for the notebook.



**Lind part # MO1930-1003**

Voltage spikes or surges occurring on the voltage line will be filtered by the adapter eliminating the possibility of damage to the notebook due to supply voltage variations. The Lind Automobile Power Adapter is epoxy potted and housed in a recently developed ABS case for durability and sealed to protect the Adapter from moisture and high humidity.

### Technical Information

INPUT VOLTAGE	12 to 32 VDC
OUTPUT POWER	19V @ 3.0A
WEIGHT	370 gram
SIZE	13.5 x 7.5 x 2.5 cm
INPUT CABLE	92cm, 18 awg, Cig Plug
OUTPUT CABLES	92cm, 20 awg, DC Plug
INPUT FUSE	15 A inside adapter
WARRANTY	3 Year
OPERATING TEMPERATURE	-20 to +40 °C
STORAGE TEMPERATURE	-40 to +85 °C

### Safety Information

Output Short Circuit Shut Down  
 Output Over Current Shut Down  
 Output High Voltage Limit  
 Input Power Limit  
 Input Reverse Polarity Protection  
 Over Temperature Shut-Down  
 Low Input Voltage Shut-Down  
 High Input Voltage Shut-Down  
 Automatic Reset of Safety Shut-Down  
 On-Board Fuse Link



Unit 1, Compton Place,  
 Surrey Avenue, Camberley,  
 Surrey GU15 3DX,  
 UK

Tel: +44 1276 686707  
 Fax: +44 1276 684329  
 Email: [sales@rugged-systems.com](mailto:sales@rugged-systems.com)  
 Web: [www.rugged-systems.com](http://www.rugged-systems.com)



USA Office:  
 6414 Cambridge Street  
 Minneapolis, MN 55408  
 Phone: +1 (952) 927 6303  
 Fax: +1 (952) 927 7740  
 Web: [www.lindelectronics.com](http://www.lindelectronics.com)

European Office:  
 Astenweg 4/2  
 73765 Neuhausen, Germany  
 Phone: +49 7158 987 5460  
 Fax: +49 7158 987 5416  
 Email: [meisele@lindelectronics.com](mailto:meisele@lindelectronics.com)