

Rugged DC/DC Auto Power Adapter

**For Panasonic Toughbooks up to 90 Watts
15V @ 6.0A**

The Lind Automobile Power Adapter delivers a true continuous 95 Watt power output to your Toughbook. The Adapter allows the device to be operated and its internal battery to be recharged from any 12-32 VDC source. Simply plug the Lind Automobile Power Adapter into the cigarette lighter socket in an automobile and into the power jack of the Toughbook. The adapter adjusts, conditions and regulates the power from the input to the correct DC voltage required for the Toughbook.

Voltage spikes or surges occurring on the voltage line will be filtered by the adapter eliminating the possibility of damage to the Toughbook due to supply voltage variations. The Lind Automobile Power Adapter is epoxy potted and housed in a recently developed ABS case for durability and sealed to protect the Adapter from moisture and high humidity.



Lind part # PA1555-731

Technical Information

Safety Information

INPUT VOLTAGE	12 to 32 VDC
OUTPUT POWER	15V @ 6.0A
WEIGHT	370 gram
SIZE	13.5 x 7.5 x 2.5 cm
INPUT CABLE	92cm, 18 awg, Cig Plug
OUTPUT CABLES	92cm, 20 awg, black DC Plug 92cm, 20 awg, yellow DC Plug
INPUT FUSE	15 A inside adapter
WARRANTY	3 Year
OPERATING TEMPERATURE	-20 to +40 °C
STORAGE TEMPERATURE	-40 to +85 °C

Output Short Circuit Shut Down
Output Over Current Shut Down
Output High Voltage Limit
Input Power Limit
Input Reverse Polarity Protection
Over Temperature Shut-Down
Low Input Voltage Shut-Down
High Input Voltage Shut-Down
Automatic Reset of Safety Shut-Down
On-Board Fuse Link



Unit 1, Compton Place,
Surrey Avenue, Camberley,
Surrey GU15 3DX,
UK

Tel: +44 1276 686707
Fax: +44 1276 684329
Email: sales@rugged-systems.com
Web: www.rugged-systems.com



USA Office:
6414 Cambridge Street
Minneapolis, MN 55408
Phone: +1 (952) 927 6303
Fax: +1 (952) 927 7740
Web: www.lindelectronics.com

European Office:
Asterweg 4/2
73765 Neuhausen, Germany
Phone: +49 7158 987 5460
Fax: +49 7158 987 5416
Email: meisele@lindelectronics.com